

Pioneer Dj

DDJ-SR2

SERATO DJ CONTROLLER

HARMONIC CONTROL

DEDICATED CONTROLS FOR THE LATEST SERATO DJ FEATURES

KEY SHIFT, KEY SYNC AND PITCH PLAY CONTROLS

MULTICOLOURED PERFORMANCE PADS

LIGHTWEIGHT, PORTABLE DESIGN

NEEDLE SEARCH PAD

DUAL LEVEL METER

MAINS OR USB POWER

MULTIPLE CONNECTIVITY

SERATO DJ ENABLED

INCLUDES PITCH 'N TIME DJ EXPANSION PACK

SERATO DVS UPGRADE READY

serato  **DJ**



DDJ-SR2 SERATO DJ CONTROLLER

GET HANDS-ON WITH THE PITCH 'N TIME DJ EXPANSION PACK

PRODUCT FEATURES



KEY SHIFT, KEY SYNC AND PITCH PLAY CONTROLS

Use the dedicated controls to get hands-on with the latest features in Serato DJ, including the Pitch 'n Time DJ Expansion Pack, with Key Shift, Key Sync and Pitch Play controls.



MULTICOLOURED PERFORMANCE PADS

Use the large, multicoloured tactile Performance Pads to trigger Hot Cues, Roll and Sampler. Hit the pads and watch their colours change as they indicate the selected pad mode and playing status.



LIGHTWEIGHT AND PORTABLE

Thanks to the high-quality aluminium-finish top panel and jog wheels, the DDJ-SR2 is approximately 18 per cent lighter than the DDJ-SR.



INCLUDES PITCH 'N TIME DJ EXPANSION PACK

The DDJ-SR2 is Serato DJ Enabled and Serato DVS Upgrade Ready, plus it includes the Pitch 'n Time DJ Expansion Pack.

MAIN SPECIFICATIONS

Software	Serato DJ
Frequency range	20 Hz ~ 20 kHz
S/N ratio	105 dB (USB)
Sampling rate	44.1 kHz
A/D, D/A converter	24-bit
Total harmonic distortion	0.003 % (USB)
Input terminals	LINE/PHONO × 2 (RCA × 2) MIC × 1 (1/4-inch TS JACK)
Output terminals	MASTER × 2 (XLR × 1, RCA × 1) BOOTH OUT × 1 (1/4-inch TRS JACK) PHONES × 2 (FRONT 6.3-mm 1/4-inch TRS JACK × 1, 3.5-mm 1/8-inch STEREO MINI JACK × 1)
Other ports	USB (TypeB) × 1
Dimensions (W x D x H)	553.0 mm × 334.5 mm × 65.1 mm
Unit weight	3.7 kg

SERATO DJ SYSTEM REQUIREMENTS

Supported operating systems

Windows	Windows® 10, 8.1, 7 (latest service pack)
Mac	macOS Sierra 10.12 (latest update) OS X 10.11, 10.10 (latest update)
CPU	intel® processor Core™ i7 and i5 1.07 GHz or higher
Memory	4GB or more of RAM



1 MULTIPLE CONNECTIVITY

Control trims, EQs and channel faders for audio from media players or turntables thanks to dual line and phono inputs. Use the booth and two master outputs to connect to PA equipment.

2 NEEDLE SEARCH PAD

Instantly jump to a specific part of a track with a simple touch of the pad.

3 USB OR MAINS POWER

Choose your preferred source.



Disclaimer: specifications and price are subject to change. * Serato DJ is a registered trademark of Serato Audio Research Ltd. * Mac, macOS or OS X are trademarks of Apple Inc., registered in the US and other countries. * Windows® is a registered trademark of Microsoft Corporation in the US and other countries. * Intel® and Intel Core™ are registered trademarks of Intel Corporation in the US and other countries. * Other stated company names, product names, technology names, etc. are the trademarks or registered trademarks of their respective owners.

We've made every effort to show the product accurately, but colours and typography might be different in reality. Features and specifications are correct at the time of printing but are subject to change. Please speak to your Pioneer DJ dealer to make sure the product meets your needs.

Pioneer DJ Europe Ltd | Anteros Building, Odyssey Business Park, West End Road, South Ruislip, HA4 6QQ, UK | +44 (0) 203 761 7220
Pioneer DJ Americas, Inc | 2050 W. 190th Street, Suite 109, CA 90504, Torrance, USA | +1 (424) 488-0480
Pioneer DJ Corporation | 6-F, Yokohama i-Mark Place, 4-4-5 Minatomirai, Nishi-ku, Yokohama, Kanagawa 220-0012 Japan | +81 045-522-5400